



1. THIS CONTRACTOR SHALL PROVIDE LUGS FOR TERMINATION OF CONDUCTOR SIZES SHOWN.
2. PROVIDE A #2 AWG I.G. CONDUCTOR FOR IMAGER. SEE "RISER - ISOLATED EQUIPMENT GROUND FOR IMAGER, (ROOM #207)". (ADJUST CONDUIT SIZE ACCORDINGLY).
3. CONSTRUCT TEMPORARY SUPPORT STRUCTURE FOR NEW SERVICE EQUIPMENT. AFTER EXTERIOR WALL IS CONSTRUCTED, ATTACH SERVICE EQUIPMENT TO WALL. COORDINATE INSTALLATION OF NEW SERVICE EQUIPMENT WITH UTILITY COMPANY.

N.T.S.

- ① NEW (4) 4" GRSC - 4 #500KCM & 1 #3/0 GND. EACH. (SEE NOTE #2 FOR ADDITIONAL REQUIREMENTS).
- ② NEW (3) 3 1/2" GRSC - 4 #400KCM & 1 #1/0 GND. EACH. (SEE NOTE #2 FOR ADDITIONAL REQUIREMENTS).
- ③ NEW EMERGENCY GENERATOR SHUTDOWN BREAK GLASS CONTROL STATION. ACTIVATION OF THIS SHALL SHUT DOWN GENERATOR & STOP FUEL SUPPLY. PROVIDE NAMEPLATE, "GENERATOR EMERGENCY SHUTDOWN".
- ④ NEW 2"CA - 4 #3/0 & 1 #6 GND. TEMPORARY FEEDER. REMOVE AFTER CONSTRUCTION IS COMPLETE.
- ⑤ EXISTING 200A/3P F.D.S. ON EXTERIOR WALL. REMOVE AFTER CONSTRUCTION IS COMPLETE.

E-3 10 of 39