

1011 N Causeway Blvd, Suite 19 ◆ Mandeville, Louisiana 70471 ◆ Phone: 985.624.5001 ◆ Fax: 985.624.5303

January 2022

Property Owner: Kim Quetel

Property Address: 209 Lapaz, Lake City, FL 32024

RE: Photovoltaic System Roof Installations

I have reviewed the existing structure referenced above to determine the adequacy of the existing structure support the proposed installation of an array of solar panels on the roof.

Based on my review, the existing structure is adequate to support the proposed solar panel installation. This assessment is based on recent on-site inspection by SunPro Solar inspectors and photographs of the existing structure. The photovoltaic system is designed to withstand uplift and downward forces; our assessment is regarding the structure's support of the array. Stresses induced by the introduction of individual mount loads on the rafters or truss top chord are within acceptable limits as shown on the attached calculations. The structural considerations used in our review and assessment include the following:

Evaluation Criteria:

Applied Codes: ASCE 7-16 FBC 2020 NEC 2017

Risk Category: II

Design Wind Speed (3-second gust): 165 MPH

Wind Exposure Category: C Ground Snow Load:0 PSF Seismic Design Category: D

Existing Structure:

Roof Material: Shingle

Roofing Structure: 2x Truss Top Chord @ 24" O.C.

Roof Slope: 3/12

Connection of Array to Structure:

Manufacturer: UNIRAC Mount: Flashloc Comp Kit

Mounting Connection: Flashloc Comp Kit 5/16" lag screw w/min 2.5" embedment into framing

Zone 1: 2 rails 2'-0" o.c. mounts Zone 2: 3 rails 4'-0" o.c. mounts Zone 3: 3 rails 4'-0" o.c. mounts

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649 Mo. 71950

*
STATE OF

ONAL

This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL Infrastructure®

Page 2 of 3

Effect of the Solar Array on Structure Loading:

Gravity Loads:

Per IBC Section 1607.12.5.1, the areas of the roof where solar panels are located are considered inaccessible, and therefore not subject to roof live loading. Live load in these areas is replaced by the dead load of the solar array, 3 psf. The total gravity load on the structure is therefore reduced and the structure may remain unaltered. Connections of the mounts to the underlying structure are to be installed in a staggered pattern, except at the array ends, to distribute the loading evenly to the roof structure. The stresses within the rafters or truss top chord due to the introduction of discrete mount loads are within acceptable l imits, as shown on the attached calculations.

Wind Load:

The solar panel array will be flush mounted (no more than 6" above the surrounding roof surface, and parallel to the roof surface. Any additional wind loading on the structure due to the presence of the array is negligible. The array structure is designed by the manufacturer to withstand uplift and downward forces resulting from wind and snow loads. The attached calculations verify the capacity of the connection of the solar array to the roof to resist uplift due to wind loads, the governing load case.

Snow Load:

The reduced friction of the glass surface of the solar panels allows for the lower slope factor (C_s) per Section 7.4 of ASCE 7-16 resulting in a reduced design snow load for the structure. This analysis conservatively considered the snow load to be unchanged.

Seismic Load:

Analysis shows that additional seismic loads due to the array installation will be small. Even conservatively neglecting the wall materials, the solar panel installation represents an increase in the total weight of the roof and corresponding seismic load of less than 10%. This magnitude of additional forces meets the requirements of the exception in Section 11B.4 of ASCE 7-16. The existing lateral force resisting system of the structure is therefore allowed to remain unaltered.



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL Engineering

Architecture ♦ Engineering ♦ Construction

Page 3 of 3

Conclusion:

To the best of my professional knowledge and belief, the subject construction and photovoltaic system installation will be in compliance with all state and local building codes and guidelines in effect at the time of our review.

Limitations:

Engineer's assessment of the existing structure is based on recent field reports and current photographs of the elements of the structure that were readily accessible at the time of inspection. The design of the solar panel racking (mounts, rails, connectors, etc.), connections between the racking and panels, and electrical engineering related to the installation are the responsibility of others. The photovoltaic system installation must be by competent personnel in accordance with manufacturer recommendations and specifications and should meet or exceed industry standards for quality. The contractor is responsible for ensuring that the solar array is installed according to the approved plans and must notify the engineer of any undocumented damage or deterioration of the structure, or of discrepancies between the conditions depicted in the approved plans and those discovered on site so that the project may be reevaluated and altered as required. Engineer does not assume any responsibility for improper installation of the proposed photovoltaic system.



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

Uplift and Wind Downforce Calculation Summary (ASCE 7-16) Mount, Rack, & Panel Proportioning Point Load Check and Rafter Stress Analysis

Property Owner:	Kim Quetel	Max. Individu	ial Panel Dimension	S
Project Address:	209 Lapaz	Length (in)	Width (in)	Area (sf)
City, State:	Lake City, FL 32024	77	39	20.85

Building Characteristics, Design Input, and Adjustment Factors				
Roof Dimensions: Length:	1	Greater Dimension 84		
Width:		Least Dimension: 47		
Roof Height (h):	15	Fig 30.4-1, valid under 60°		
Pitch: 3 on 12 =	14.0°	Must be less than 45° ✓		
Roof Configuration	Gable			
Roof Structure	2x Truss Top	Chord		
Roof Material	Plywood			
Risk Category:	II			
Basic Wind Speed:	165	From 26.5-1		
Exposure Category:	С	Fig. 26.7		
Topographic Factor (K _{zt})	1.0	Fig. 26.8-1		
Wind Pressure @ h=30, p _{net30}	See Table Bel	Fig. 30.4-1		
Ht. & Exposure Adjustment (λ)	0.82	Fig. 30.4-1		
Adjusted Wind Pressures, p _{net}	See Table Bel	elow Eq. 30.4-1		
Effective Wind Area (sf):		(Area per individual mount)		
Roof Zone Strip	a), in ft, Fig. 3	30.4-1, Note 5		
1 - Least Roof Horizontal Dimension (L or V	V) x 0.10	4.7		
2 - Roof Height x 0.4		6		
3 - Least Roof Horizontal Dimension (L or V	V) x 0.04	1.88		
4 - Least of (1) and (2)		4.7		
5 - Greater of (3) and (4)		4.7		
6 - Greater of (5) and 3 feet		a= 4.7		



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

	Net Design Pressures, p _{net} (Fig 30.4-1), Comp Uplift (-psf)		Factored Pressure		
		P _{30net}	IK _{zt} P _{30net}	(0.6W, ASCE 7-16)	θ
gable /hip /flat					
	Zone 1 & 2e	85.4	70.1	42.0	
	Zone 2n,2r,3e	124.7	102.2	61.3	7° < θ ≤ 20°
	Zone 3r	148.2	121.5	72.9	
Gable					
					-0.5
Hip					_ 0 0 20 < 0 ≤ 27 0
					27 - 8 - 45

This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this

document are not considered

signed and sealed and the


signature must be verified

on any electronic copies.

Snow Load			
Ground Snow Load, pg	0.0	From ASCE 7 or AHJ	
Terrain Category:	С	Para 6.5.6.3	
Exposure	Partial		
Exposure FactorCe	1.0	Table 7-2	
Thermal Factor, Ct	1.0	Table 7-3	
Importance Factor, I _s	1.0	Table 1.5.2	
Roof Configuration	Gable		
Roof Slope	14.0°		
Distance from Eave to Ridge	23.5		
p _m , Minimum required Snow Load	0.00 psf	Para. 7.3.4	
pf, Calculated Snow Load	0.00	Eq. 7.3-1	
pf, Design Snow Load	0.00 psf		

	Rail & Mount Selection (FS=3.0)		
Manufacturer:	Unirac	Allowable Mount Spacing by Uplift Pressure	
Model:	Flashloc Comp Kit	< 37 psf: 2 rails, mounts @ 4 ft. o.c.	
Substrate	Wood Rafters/Truss Top Chord	37 to 56 psf: 2 rails, mounts @ 2 ft. o.c.	
Connector:	5/16" x 4" Lag Screw	56 to 75 psf: 3 rails, mounts @ 4 ft. o.c.	
		75 to 112 psf: 3 rails, mounts @ 2 ft. o.c.	
Allowable Uplift:	480 lb., max.	112 to 150 psf: 4 rails, mounts @ 2 ft. o.c.	
	•	> 150 psf: Mount capacity exceeded	

	Rail & Mount Layout by Zone				
Zone 1:	2 rails, mounts @ 2 ft. o.c.	Zone 2r:	3 rails, mounts @ 4 ft. o.c.		
Zone 1':	N/A	Zone 3:	N/A		
Zone 2:	N/A	Zone 3e:	3 rails, mounts @ 4 ft. o.c.		
Zone 2e:	2 rails, mounts @ 2 ft. o.c.	Zone 3r:	3 rails, mounts @ 4 ft. o.c.		
Zone 2n:	Zone 2n: 3 rails, mounts @ 4 ft. o.c.				
	(From rail analysis, allowable spacing and number of rails are controlled by individual mount pullout before rail bending)				



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

NEW PHOTOVOLTAIC SYSTEM 11.63 KW DC 209 LAPAZ, LAKE CITY, FL 32024

GENERAL NOTES

1.1.1 PROJECT NOTES:

1.1.2 THIS PHOTOVOLTAIC (PV) SYSTEM SHALL COMPLY WITH THE NATIONAL ELECTRIC CODE (NEC) ARTICLE 690, ALL MANUFACTURERS'S LISTING AND INSTALLATION INSTRUCTIONS, AND THE RELEVANT CODES AS SPECIFIED BY THE AUTHORITY HAVING JURISDICTION'S (AHJ) APPLICABLE CODES.
1.1.3 THE UTILITY INTERCONNECTION APPLICATION MUST BE APPROVED AND PV SYSTEM INSPECTED PRIOR TO PARALLEL OPERATION
1.1.4 GROUND FAULT DETECTION AND INTERRUPTION (GFDI) DEVICE IS

INTEGRATED WITH THE MICRO-INVERTER IN ACCORDANCE WITH NEC 690.41(B) 1.1.5 ALL PV SYSTEM COMPONENTS; MODULES, UTILITY-INTERACTIVE INVERTERS, AND SOURCE CIRCUIT COMBINER BOXES ARE IDENTIFIED AND LISTED FOR USE IN PHOTOVOLTAIC SYSTEMS AS REQUIRED BY NEC 690.4: PV MODULES: UL1703, IEC61730, AND IEC61215, AND NFPA 70 CLASS C FIRE INVERTERS: UL 1741 CERTIFIED, IEEE 1547, 929, 519 COMBINER BOX(ES): UL 1703 OR UL 1741 ACCESSORY

1.1.6 MAX DC VOLTAGE CALCULATED USING MANUFACTURER PROVIDED TEMP COEFFICIENT FOR VOC. IF UNAVAILABLE, MAX DC VOLTAGE CALCULATED ACCORDING TO NEC 690.7.

1.1.7 ALL INVERTERS, PHOTOVOLTAIC MODULES, PHOTOVOLTAIC PANELS, AND SOURCE CIRCUIT COMBINERS INTENDED FOR USE IN A PHOTOVOLTAIC POWER SYSTEM WILL BE IDENTIFIED AND LISTED FOR THE APPLICATION PER 690.4. SHALL BE INSTALLED ACCORDING TO ANY INSTRUCTIONS FROM LISTING OR LABELING [NEC 110.3].

1.1.8 ALL SIGNAGE TO BE PLACED IN ACCORDANCE WITH LOCAL BUILDING CODE. IF EXPOSED TO SUNLIGHT, IT SHALL BE UV RESISTANT. ALL PLAQUES AND SIGNAGE WILL BE INSTALLED AS REQUIRED BY THE NEC AND AHJ.

1.2.1 SCOPE OF WORK:

1.2.2 PRIME CONTRACTOR IS RESPONSIBLE FOR THE DESIGN AND SPECIFICATIONS OF THE GRID-TIED PHOTOVOLTAIC SYSTEM RETROFIT. PRIME CONTRACTOR WILL BE RESPONSIBLE FOR COLLECTING EXISTING ONSITE REQUIREMENTS TO DESIGN, SPECIFY, AND INSTALL THE EXTERIOR ROOF-MOUNTED PORTION OF THE PHOTOVOLTAIC SYSTEMS DETAILED IN THIS DOCUMENT

1.3.1 WORK INCLUDES:

1.3.2 PV RACKING SYSTEM INSTALLATION - UNIRAC SOLAR

1.3.3 PV MODULE AND INVERTER INSTALLATION - LG ELECTRONICS LG375N1C-A6 / ENPHASE IQ7PLUS-72-2-US INVERTER

1.3.4 PV EQUIPMENT ROOF MOUNT

1.3.5 PV SYSTEM WIRING TO A ROOF-MOUNTED JUNCTION BOX

1.3.6 PV LOAD CENTERS (IF INCLUDED)

1.3.7 PV METERING/MONITORING (IF INCLUDED)

1.3.8 PV DISCONNECTS

1.3.9 PV GROUNDING ELECTRODE & BONDING TO (E) GEC

1.3.10 PV FINAL COMMISSIONING

1.3.11 (E) ELECTRICAL EQUIPMENT RETROFIT FOR PV

1.3.12 SIGNAGE PLACED IN ACCORDANCE WITH LOCAL BUILDING CODE

PROJECT INFORMATION

OWNER

NAME: KIM QUETEL

PROJECT MANAGER
NAME: SHAHIN HAYNES
PHONE: 8665071461

CONTRACTOR NAME

MARC JONES CONSTRUCTION, LLC DBA SUNPRO SOLAR

PHONE: 5052180838



SCOPE OF WORK

SYSTEM SIZE: STC:31 X 375W= 11.63 kW DC

PTC: 31 x 347.3W = 10.77 kW DC (31) LG ELECTRONICS LG375N1C-A6 (31) ENPHASE IQ7PLUS-72-2-US

ATTACHMENT TYPE: ROOF MOUNT

MSP UPGRADE: YES

UTILITY METER UPGRADE: YES

AUTHORITIES HAVING JURISDICTION

BUILDING: COLUMBIA COUNTY ZONING: COLUMBIA COUNTY UTILITY: CLAY ELECTRIC CO-OP

DESIGN SPECIFICATION

OCCUPANCY: II

CONSTRUCTION: SINGLE-FAMILY ZONING: RESIDENTIAL

GROUND SNOW LOAD: REFER STRUCTURAL LETTER WIND EXPOSURE: REFER STRUCTURAL LETTER

WIND SPEED: 165MPH

APPLICABLE CODES & STANDARDS

BUILDING: IBC 2018, IRC 2018, FBC 2020 (7TH EDITION)

ELECTRICAL: NEC 2017 FIRE: IFC 2020

VICINITY MAP



SATELLITE VIEW



SHEET INDEX

G-001	COVER PAGE
G-002	NOTES
A-101	SITE PLAN
A-102	ELECTRICAL PLAN
A-103	ATTACHMENT PLAN
A-104	STRUCTURAL PLAN
E-601	LINE DIAGRAM
E-602	ELECTRICAL CALCULATIONS
E-603	PLACARD
E-604	LOAD CALCULATIONS
R-001	RESOURCE DOCUMENT
R-002	RESOURCE DOCUMENT
R-003	RESOURCE DOCUMENT
R-004	RESOURCE DOCUMENT
R-005	RESOURCE DOCUMENT
R-006	RESOURCE DOCUMENT
R-007	RESOURCE DOCUMENT
R-008	RESOURCE DOCUMENT

SUNPR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490
PROJECT NAME & ADDRESS

KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649

SHEET TITLE

COVER PAGE

DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

G-001

2.1.1 SITE NOTES:

- 2.1.2 A LADDER WILL BE IN PLACE FOR INSPECTION IN COMPLIANCE WITH CONVENTION IF THREE PHASE C OR L3- BLUE, OSHA REGULATIONS.
- 2.1.3 THE PV MODULES ARE CONSIDERED NON-COMBUSTIBLE AND THIS SYSTEM IS A UTILITY INTERACTIVE SYSTEM WITH NO STORAGE BATTERIES.
- 2.1.4 THE SOLAR PV INSTALLATION WILL NOT OBSTRUCT ANY PLUMBING. MECHANICAL, OR BUILDING ROOF VENTS.
- 2.1.5 PROPERACCESS AND WORKING CLEARANCE AROUND EXISTING AND PROPOSED ELECTRICAL EQUIPMENT WILL BE PROVIDED AS PERSECTION NEC 110.26.
- 2.1.6 ROOF COVERINGS SHALL BE DESIGNED, INSTALLED, AND MAINTAINED IN ACCORDANCE WITH THIS CODE AND THE APPROVED MANUFACTURER'S INSTRUCTIONS SUCH THAT THE ROOF COVERING SERVES TO PROTECT THE BUILDING OR STRUCTURE. 2.2.1 EQUIPMENT LOCATIONS:
- 2.2.2 ALL EQUIPMENT SHALL MEET MINIMUM SETBACKS AS REQUIRED BY 2.5.5 EQUIPMENT GROUNDING CONDUCTORS SHALLBE SIZED NEC 110.26.
- 2.2.3 WIRING SYSTEMS INSTALLED IN DIRECT SUNLIGHT MUST BE RATED MANUFACTORERS' INSTRUCTIONS. FOR EXPECTED OPERATING TEMPERATURE AS SPECIFIED BY NEC 690.31 2.5.6 EACH MODULE WILL BE GROUNDED USING WEEB (A),(C) AND NEC TABLES 310.15 (B)(2)(A) AND 310.15 (B)(3)(C).
- 2.2.4 JUNCTION AND PULL BOXES PERMITTED INSTALLED UNDER PV MODULES ACCORDING TO NEC 690.34.
- 2.2.5 ADDITIONAL AC DISCONNECT(S) SHALL BE PROVIDED WHERE THE INVERTER IS NOT WITHIN SIGHT OF THE AC SERVICING DISCONNECT. 2.2.6 ALL EQUIPMENT SHALL BE INSTALLED ACCESSIBLE TO QUALIFIED PERSONNEL ACCORDING TO NEC APPLICABLE CODES.
- 2.2.7 ALL COMPONENTS ARE LISTED FOR THEIR PURPOSE AND RATED FOR OUTDOOR USAGE WHEN APPROPRIATE.

2.3.1 STRUCTURAL NOTES:

- 2.3.2 RACKING SYSTEM & PV ARRAY WILL BE INSTALLED ACCORDING TO CODE-COMPLIANT INSTALLATION MANUAL. TOP CLAMPS REQUIRE A DESIGNATED SPACE BETWEEN MODULES, AND RAILS MUSTALSO EXTEND A MINIMUM DISTANCE BEYOND EITHER EDGE OF THE ARRAY/SUBARRAY, ACCORDING TO RAI MANUFACTURER'S INSTRUCTIONS.
- 2.3.3 JUNCTION BOX WILL BE INSTALLED PER MANUFACTURERS' SPECIFICATIONS. IF ROOF-PENETRATING TYPE. IT SHALL BE FLASHED & SEALED PER LOCAL REQUIREMENTS.
- 2.3.4 ROOFTOP PENETRATIONS FOR PV RACEWAY WILLBE COMPLETED AND SEALED W/ APPROVED CHEMICAL SEALANT PER CODE BY A LICENSED CONTRACTOR.
- 2.3.5 ALL PV RELATED ROOF ATTACHMENTS TO BE SPACED NO GREATER THAN THE SPAN DISTANCE SPECIFIED BY THE RACKING MANUFACTURER.
- 2.3.6 WHEN POSSIBLE, ALL PV RELATED RACKING ATTACHMENTS WILL BE STAGGERED AMONGST THE ROOF FRAMING MEMBERS.

2.4.1 WIRING & CONDUIT NOTES:

- 2.4.2 ALL CONDUIT AND WIRE WILL BE LISTED AND APPROVED FOR THEIR PURPOSE. CONDUIT AND WIRE SPECIFICATIONS AREBASED ON MINIMUM CODE REQUIREMENTS AND ARE NOT MEANT TO LIMIT UP-SIZING.
- 2.4.3 CONDUCTORS SIZED ACCORDING TO NEC 690.8, NEC 690.7.
- 2.4.4 VOLTAGE DROP LIMITED TO 1.5%.
- 2.4.5 DC WIRING LIMITED TO MODULE FOOTPRINT. MICROINVERTER WIRING SYSTEMS SHALL BE LOCATED AND SECURED UNDER THE ARRAY W/ SUITABLE WIRING CLIPS.

2.4.6 AC CONDUCTORS COLORED OR MARKED AS FOLLOWS: PHASE A OR L1- BLACK PHASE B OR L2- RED, OR OTHER YELLOW, ORANGE**, OR OTHER CONVENTION NEUTRAL-WHITE OR GREY IN 4-WIRE DELTA CONNECTED SYSTEMS THE PHASE WITH HIGHER VOLTAGE TO BE MARKED ORANGE [NEC 110.15].

2.5.1 GROUNDING NOTES:

THEIR PURPOSE, AND GROUNDING DEVISES EXPOSED TO THE ELEMENTS SHALL BE RATED FOR SUCH USE. 2.5.3 PV EQUIPMENT SHALL BE GROUNDED ACCORDING TO NEC 690.43 AND MINIMUM NEC TABLE 250.122. 2.5.4 METAL PARTS OF MODULE FRAMES, MODULE RACKING, AND ENCLOSURES CONSIDERED GROUNDED IN ACCORD WITH 250.134 AND 250.136(A).

2.5.2 GROUNDING SYSTEM COMPONENTS SHALL BE LISTED FOR

ACCORDING TO NEC 690.45 AND MICROINVERTER

GROUNDING CLIPS AS SHOWN IN

MANUFACTURERDOCUMENTATION AND APPROVED BY THE AHJ. IF WEEBS ARE NOT USED, MODULE GROUNDING LUGS MUST BE INSTALLED AT THE SPECIFIED GROUNDING LUG HOLES PER THE MANUFACTURERS' INSTALLATION REQUIREMENTS.

2.5.7 THE GROUNDING CONNECTION TO A MODULE SHALL BE ARRANGED SUCH THAT THE REMOVAL OFA MODULE DOES NOT INTERRUPT A GROUNDING CONDUCTOR TO ANOTHER MODULE. 2.5.8 GROUNDING AND BONDING CONDUCTORS, IF INSULATED, SHALL BE COLORED GREEN OR MARKED GREEN IF #4 AWG OR LARGER [NEC 250.119]

2.5.9 THE GROUNDING ELECTRODE SYSTEM COMPLIES WITH NEC 690.47 AND NEC 250.50 THROUGH 250.106. IF EXISTING SYSTEM IS INACCESSIBLE, OR INADEQUATE, A GROUNDING ELECTRODE SYSTEM PROVIDED ACCORDING TO NEC 250, NEC 690.47 AND

2.5.10 GROUND-FAULT DETECTION SHALL COMPLY WITH NEC 690.41(B)(1) AND (2) TO REDUCE FIRE HAZARDS

2.6.1 DISCONNECTION AND OVER-CURRENT PROTECTION NOTES:

2.6.2 DISCONNECTING SWITCHES SHALL BE WIRED SUCH THAT WHENTHE SWITCH IS OPENED THE CONDUCTORS REMAINING ENERGIZED ARECONNECTED TO THE TERMINALS MARKED "LINE SIDE" (TYPICALLY THE UPPER TERMINALS). 2.6.3 DISCONNECTS TO BE ACCESSIBLE TO QUALIFIED UTILITY PERSONNEL, BE LOCKABLE, AND BE A VISIBLE-BREAK SWITCH 2.6.4 PV SYSTEM CIRCUITS INSTALLED ON OR IN BUILDINGS SHALL INCLUDE A RAPID SHUTDOWN FUNCTION TO REDUCE SHOCK HAZARD FOR EMERGENCY RESPONDERS IN ACCORDANCE WITH 690.12(A) THROUGH (D). 2.6.5 ALL OCPD RATINGS AND TYPES SPECIFIED ACCORDING TO NEC 690.8, 690.9, AND 240. 2.6.6 MICROINVERTER BRANCHES CONNECTED TO A SINGLE BREAKER OR GROUPED FUSES IN ACCORDANCE WITH NEC

2.6.7 IF REQUIRED BY AHJ, SYSTEM WILL INCLUDE ARC-FAULT CIRCUIT PROTECTION ACCORDING TO NEC 690.11 AND UL1699B.

110.3(B).

2.7.1 INTERCONNECTION NOTES:

2.7.2 LOAD-SIDE INTERCONNECTION SHALL BE IN ACCORDANCE WITH INEC 705.12 (B)] 2.7.3 THE SUM OF THE UTILITY OCPD AND INVERTER CONTINUOUS OUTPUT MAY NOT EXCEED 120% OF BUSBAR RATING [NEC 705.12(B)(2)(3)(b)]. 2.7.4 THE SUM OF 125 PERCENT OF THE POWER SOURCE(S) OUTPUT CIRCUIT CURRENT AND THE RATING OF THE OVERCURRENT DEVICE PROTECTING THE BUSBAR SHALL NOT EXCEED 120 PERCENT OF THE AMPACITY OF THE BUSBAR, PV DEDICATED BACKFEED BREAKERS MUST BE LOCATED OPPOSITE END OF THE BUS FROM THE UTILITY SOURCE OCPD [NEC 705.12(B)(2)(3)]. 2.7.5 AT MULTIPLE ELECTRIC POWER SOURCES OUTPUT COMBINER PANEL, TOTAL RATING OF ALL

OVERCURRENT DEVICES SHALL NOT EXCEED AMPACITY OF BUSBAR. HOWEVER, THE COMBINED OVERCURRENT DEVICE MAY BE EXCLUDED ACCORDING TO NEC 705.12 (B)(2)(3)(C). 2.7.6 FEEDER TAP INTERCONECTION (LOADSIDE) ACCORDING TO NEC 705.12 (B)(2)(1) 2.7.7 SUPPLY SIDE TAP INTERCONNECTION ACCORDING TO NEC 705.12 (A) WITH SERVICE ENTRANCE **CONDUCTORS IN ACCORDANCE WITH NEC 230.42** 2.7.8BACKFEEDING BREAKER FOR ELECTRIC POWER SOURCES OUTPUT IS EXEMPT FROM ADDITIONAL FASTENING [NEC 705.12 (B)(5)].

CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490


PROJECT NAME & ADDRESS KIM QUETEL

209 LAPAZ.LAKE CITY. FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649


SHEET TITLE


NOTES

DRAWN DATE	1/21/2022	
DRAWN BY	VI	

SHEET NUMBER

G-002





CONTRACTOR SUNPR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490


PROJECT NAME & ADDRESS
KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Nestor J. Houghton, P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649

SHEET TITLE

ELECTRICAL PLAN

DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

A-102

Note 1: Windspeed value is design 3-sec gust in accordance with ASCE 7-16

Note 2: a)Lag bolt shall be mounted into rafters

b)Notify Engineer immediately if conditions differ or prevent installation per plan.


Note 3: These drawings were prepared under my supervison. I have researched the code and to the best of my knowledge And belief, these drawings comply with the 2020 Florida Building Code.


Note 4: Installer shall adjust mount spacing by zone to match prescribed values on engineer's calculation letter

- CLAMP - UNIRAC FLASHLOC - RAIL - RAFTER

- TOTAL MOUNT

ARRAY 1 TILT- 14 DEG AZIMUTH - 268 DEG





ARRAY 2 TILT- 14 DEG AZIMUTH - 268 DEG

ARRAY 3 TILT- 15 DEG AZIMUTH - 178 DEG

1 ATTACHMENT PLAN

SCALE:1/8"=1'-0"

CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490

PROJECT NAME & ADDRESS KIM QUETEL

209 LAPAZ, LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649


SHEET TITLE

ATTACHMENT PLAN

DRAWN DATE 1/21/2022 DRAWN BY VI

SHEET NUMBER

A-103



CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490

KIM QUETEL

209 LAPAZ, LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Henry I. DiFranco, Jr., P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649

SHEET TITLE

STRUCTURAL PLAN

DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

A-104

SOLAR MODULE SPECIFICATIONS		
MANUFACTURER / MODEL #	LG ELECTRONICS LG375N1C-A6	
VMP	35.3V	
IMP	10.63A	
VOC	41.8V	
ISC	11.35A	
TEMP. COEFF. VOC	-0.26%/°C	
MODULE DIMENSION	68.50"L x 41.00"W x 1.57"D (In Inch)	

INVERTER SPECIFICATIONS			WIRE /CONDUIT SCHEDULE		
MANUFACTURER / MODEL #	ENPHASE IQ7PLUS-72-2-US MICROINVERTER	TAG	DESCRIPTION		
MIN/MAX DC VOLT RATING	22V MIN/ 60V MAX		(2)#42/2 DOMEY IN ATTIC/(6)#42 THIMM 2 ON		
MAX INPUT POWER	235W-440W	┨ '	(3)#12/2 ROMEX IN ATTIC/(6)#12 THWN-2 ON EXTERIOR & (1)#6 THWN -2 / (GN)		
NOMINAL AC VOLTAGE RATING	240V/ 211-264V	$ begin{array}{c} beg$, , ,		
MAX AC CURRENT	1.21A	2	(3)#6 THWN-2 & (1)#6 THWN-2 GROUND / (GN)		
MAX MODULES PER STRING	13 (SINGLE PHASE)	3	(3)#2/0 THWN-2 / (GN)		
MAX OUTPUT POWER	290 VA	4	(1)#6 BARE GROUND		
		(GN)	GENERAL CONDUIT NOTE:		


DC SIZE 31 X 375W = 11.625 kW DC-STC AC SIZE 31X 290W = 8.990 kW AC

CONDUIT TO BE UL LISTED FOR WET LOCATIONS AND UV PROTECTED (EX. -EMT, SCH 80 PVC OR RMC)*FMC MAYBE USED IN INDOOR APPLICATIONS WHERE PERMITTED BY

(GN) GENERAL CONDUIT NOTE:

NEC ART .348

THE MAIN BREAKER OR FEEDER UNIT



NEW MSP 225A/200A RATED

CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490


PROJECT NAME & ADDRESS KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Nestor J. Houghton, P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649

SHEET TITLE

LINE DIAGRAM

DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

AMBIENT TEMPERATURE SPECS				
RECORD LOW TEMP	-5°			
AMBIENT TEMP (HIGH TEMP 2%)	34°			
CONDUIT HEIGHT	0.5"			
CONDUCTOR TEMPERATURE RATE	90°			

PERCENT OF VALUES	NUMBER OF CURRENT CARRYING CONDUCTORS
.80	4-6
.70	7-9
.50	10-20

CALCULATIONS:

1. CURRENT CARRYING CONDUCTOR

(A) <u>BEFORE IQ COMBINER PANEL</u>
AMBIENT TEMPERATURE - (34)°C ...NEC 310.15(B)(3)(c)
TEMPERATURE DERATE FACTOR - 0.96 ...NEC 310.15(B)(2)(a)
GROUPING FACTOR - 0.8...NEC 310.15(B)(3)(a)

CONDUCTOR AMPACITY

- $= (INV O/P CURRENT) \times 1.25 / A.T.F / G.F ...NEC 690.8(B)$
- $= [(11 \times 1.21) \times 1.25] / [0.96 \times 0.8]$
- = 21.66A

SELECTED CONDUCTOR - #12 THWN-2 ...NEC 310.15(B)(16)

(B) AFTER IQ COMBINER PANEL
TEMPERATURE DERATE FACTOR - 0.96
GROUPING FACTOR - 1

CONDUCTOR AMPACITY

- $= (TOTAL INV O/P CURRENT) \times 1.25 / 0.96 / 1 ... NEC 690.8(B)$
- $= [(31 \times 1.21) \times 1.25] / [0.96 \times 1]$
- = 48.84 A

SELECTED CONDUCTOR - #6 THWN-2 ...NEC 310.15(B)(16)

2. PV & BATTERY OVER CURRENT PROTECTION

...NEC 690.9(B)

= TOTAL INVERTER O/P CURRENT x 1.25 + BATTERY O/P = (31 x 1.21) x 1.25 = 46.89 A SELECTED OCPD = 50 A ...NEC 240.6

3. 120% RULE FOR BACKFEED BREAKER

...NEC 705.12(B)(2)(3)(b)

MCB + PV BREAKER <= (1.2 x BUS BAR RATING RATING)

(200 + 50) <= 1.2 x 225A

250.00 <= 270.00 HENCE OK



22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490
PROJECT NAME & ADDRESS


KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Nestor J. Houghton, P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649

SHEET TITLE ELECTRICAL CALCULATIONS


DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

WARNING: PHOTOVOLTAIC **POWER SOURCE**

SOLAR PV SYSTEM EQUIPPED WITH RAPID SHUTDOWN

TURN RAPID SHUTDOWN SWITCH TO THE 'OFF' **POSITION TO SHUT** DOWN PV SYSTEM AND REDUCE SHOCK HAZARD IN THE ARRAY



AC DISCONNECT

WARNING /!\

ELECTRIC SHOCK HAZARD

DO NOT TOUCH TERMINALS. TERMINALS ON BOTH LINE AND LOAD SIDES MAY BE ENERGIZED IN THE **OPEN POSITION**



OPERATING VOLTAGE: VOLTS OPERATING CURRENT: AMPS

> SOLAR **BREAKER**

AC COMBINER BOX

PHOTOVOLTAIC MICROINVERTERS LOCATED UNDER **EACH PV MODULE IN ROOFTOP ARRAY**

PHOTOVOLTAIC SYSTEM **EQUIPPED WITH** RAPID SHUTDOWN

RATED AC OUTPUT CURRENT: NOM. OPERATING VOLTAGE:

⚠ WARNING ⚠ DUAL POWER SOURCES

SOURCES: UTILITY GRID AND PV **SOLAR ELECTRIC SYSTEM**

KW SOLAR DISCONNECT LOCATED





CAUTION


△ WARNING **△**

INVERTER OUTPUT CONNECTION

DO NOT RELOCATE THIS

OVERCURRENT DEVICE

POWER TO THIS BUILDING IS ALSO SUPPLIED FROM THE FOLLOWING SOURCES WITH **DISCONNECTS LOCATED AS SHOWN:**



22171 MCH RD MANDEVILLE, LA 70471

CONTRACTOR

PHONE: 9152011490


PROJECT NAME & ADDRESS KIM QUETEL

209 LAPAZ, LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC



This item has been digitally signed and sealed by Nestor J. Houghton, P.E. on January 24, 2022 Printed copies of this document are not considered signed and sealed and the signature must be verified on any electronic copies.

PRINCIPAL ENGINEERING, INC. 1011 N. CAUSEWAY BLVD. STE 19 MANDEVILLE, LA 70471 985.624.5001 INFO@PI-AEC.COM FLORIDA FIRM NO. 30649

SHEET TITLE

PLACARD

DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

	Resident	tial Opti	onal Calc			9/25/1997		Job	Name	
	by: John Sakolik			Version 2011 L						
STEP 1	Article 22).82 (B) (1),(2)					Marc Jones Construc	ction, LLC Sunp	ro Sola
ft 🔻		General Lig		4,800 VA					0	
	4	Small App		6,000 VA					0	
	1	Laundry		1,500 VA				410410000 0.50	U	
	Gen.Lgt, Sm	App.& Laur	n. Load	12,300 VA				1/21/2022 6:59		
STEP 2	Article 220	.82 (C)	4			Gene	eral lighting	g, Sm. Appl. & Laundry	12,300 V	Α.
A/C Cond	1	1	Space Heating	-	QTY	Total	1			
5 ton	7,130 VA	AHU 1	-	10,800 VA	1	Heating Loa	ad	7,440 VA		
A/C#2 ▼	VA	AHU 2		VA	Qty 🔻	CU Load	d	8,330 VA		
A/C#3 ▼	VA	AHU 3	Select ▼	VA	Qty 🔻					
A/C#4 ▼	VA	AHU 4		VA	Qty ▼	Electric Space	ce Heat @ 6	5% <4, 40% >3, vs. A/C @ 100%	6 8,330 V	Α.
A/C#5 ▼	VA	AHU 5		VA	Qty 🔻					
STEP 3	Article 220).82 (B) (3)				Appliance	Demand Load	11,496 V	4
,500 VA ▼	1	Water Heat		4,500 VA						
,400 VA ▼	1	Refrigerator	r	1,400 VA			Dryer D	emand Load	5,000 V	Α.
00 VA 🔻	-	Freezer		VA			_			_
,030 VA ▼		Dishwasher	r	1,030 VA			Range D	emand Load	10,000 V	4.
90 VA 🔻	1	Disposal		VA						
00 VA 🔻	1	R / Hood		400 VA			Service	e Demand	29,848 V	4
,630 VA 🔻		Microwave		1,630 VA				B	404.4	
VA 000,	-	Microwave		VA				Demand Load	124 A	
70 VA 🔻	1	Mini Refrig		VA				Neutral Damand	78 A	
00 VA 🔻	-	Wine Clr Insta Hot		VA				Neutral Demand	/6 A	
,000 VA V	+	Ironing Cen	nter	VA VA				Min.Service Req.	125 A	
,500 VA	_	▼ Jacuzzi		VA VA				wiii.Service Req.	125 A	
H			er Pump	VA VA				Min. Feeder size	2	
H	743400	▼ Well Pu	•	1,127 VA				Min. Neutral size	4	
	select 🔻		ain Pump	VA				Eq. Grding Cond.	6	
	select -		evator	VA					Copper	
		Pool Equip.			Apply Demai	nd		hould		
		GATES			No Demand					
		Other load		VA	No Demand		Total Ap	opliance Load 11,496	5 VA	
	STEP 4 A	rticle 220.	82 (B) (3)							
		ic Clothes D		5,000 VA						
	STEP 5 A	rticle 220.								
or Nu	Electric F mber of appli	-	10,000 W	Col C deman	d	8000				
				Cooktop		Col B demar	nd			
	Check Box	for Gas Range		Cooktop		Col B demar	nd			
				Oven(s)		Col B demar				
				Oven(s)		Col B demar	nd			
		Nur	mber of appliar			Dem. Factor				
				Cooktop & Over	i Demand L	Loau			jmp1jds@comc	ast.net
	>>>>	>>>>>	>>>>>>	******	·>>>>	<<<<<<	<<<<<<	<<<<<<<<		
	Pool Panel F	eeder Calc	ulation	(See Note)	Α	В	N	Continuous	Non-continuous	
	Continuous I				704	704	0	4	Motors	
	Non-continue	ous	0	[0	0	0	1/2 hp ▼ □ 240v	select -	240
	Spa heater 1	1 kVA		[0	0		select ▼ □ 240v	select -	240
	Pool heater	3.5 ton		[0	0		select ▼	select -	240
	Pool heater	5 ton			0	0		select ▼ □ 240v	select	240
	Pool Light	select 🔻	0	·	0	0	0	select ▼ □ 240v	select -	240
	Blower	select 🔻	0		0	0	0			
	other load			240v	0	0	0	0.0	Motor Neutra	l Load
	other load			240v	0	0	0			
	Mire One	or Doc! C	dos	AMA						
	Min.Copp	er Pool Fee		AWG 30A	6 A Phase	6 A Amperes	A Neut. load	Max.Unbalanced Neutral Lo	oad	

CONTRACTOR SUNPR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490

PROJECT NAME & ADDRESS
KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

SHEET TITLE LOAD CALCULATIONS

DRAWN DATE 1/21/2022
DRAWN BY VI

SHEET NUMBER

LG NeON®2

LG370N1C-A6 LG375N1C-A6 LG380N1C-A6 Preliminary



370W

380W

The LG NeON® 2 is LG's best selling solar module and one of the most powerful and versatile modules on the market today. The cells are designed to appear all-black at a distance, and the performance warranty guarantees 90.6% of labeled power output at 25 years.









Features



Enhanced Performance Warranty

LG NeON® 2 has an enhanced performance warranty. After 25 years, LG NeON® 2 is guaranteed at least 90.6% of initial performance.



25-Year Limited Product Warranty

The NeON® 2 is covered by a 25-year limited product warranty. In addition, up to \$450 of labor costs will be covered in the rare case that a module needs to be repaired or replaced.



Solid Performance on Hot Days

LG NeON® 2 performs well on hot days due to its low temperature coefficient.



Roof Aesthetics

LG NeON® 2 has been designed with aesthetics in mind using thinner wires that appear all black at a distance.

When you go solar, ask for the brand you can trust: LG Solar

About LG Electronics USA, Inc.

LG Electronics is a global leader in electronic products in the clean energy markets by offering solar PV panels and energy storage systems. The company first embarked on a solar energy source research program in 1985, supported by LG Group's vest experience in the semi-conductor, LCD, themistry and materials industries. In 2010, LG Solar successfully released its first MonoX[®] series to the market, which is now available in 32 countries. The NeoN[®] (previous MonoX[®] NeoN), NeON[®]2, NeON[®]2, BiFacial won the "Intersolar AWARD" in 2013, 2015 and 2016, which cemonstrates LG's leadership and innovation in the solar industry.





LG370N1C-A6 LG375N1C-A6 LG380N1C-A6

General Data

Cell Properties (Material/Type)	Monocrystalline/N-type
Cell Maker	LG
Cell Configuration	60 Cells (6 x 10)
Module Dimensions (L x W x H)	1,740mm x 1,042mm x 40mm
Weight	18.6 kg
Glass (Material)	Tempered Glass with AR Coating
Backsheet (Color)	White
Frame (Material)	Anodized Aluminium
Junction Box (Protection Degree)	IP 68 with 3 Bypass Diodes
Cables (Length)	1,100mm x 2EA
Connector (Type/Maker)	MC 4/MC

Certifications and Warranty


	IEC 61215-1/-1-1/2: 2016, IEC 61730-1/2: 2016 UL 61730-1: 2017, UL 61730-2: 2017				
Certifications"	ISO 9001, ISO 14001, ISO 50001				
	OHSAS 18001				
Salt Mist Corrosion Test	IEC 61701:2012 Severity 6				
Ammonia Corrosion Test	IEC 62716 : 2013				
Module Fire Performance	Type 1 (UL 61730)				
Fire Rating	Class C (UL 790, ULC/ORD C 1703)				
Solar Module Product Warranty	25 Year Limited				
Solar Module Output Warranty	Linear Warranty*				

Temperature Characteristics			
NMOT*	,*C]	42 ± 3	
Pmax	[%/°C]	-0.34	
Voc Isc	[%/°C]	-0.26	
lsc	[%/*C]	0.03	

*FVIMOT (Nominal Module Operating Temperature): Irradiance 800 VW/m², Ambient temperature 20°C, Wind speed 1 m/s, Spectrum AM 1.5

Flectrical Properties (NMOT)

Aodel		LG370N1C-A6	LG375N1C-A6	LG380N1C-A6
Maximum Power (Pmax)	[W]	277	281	285
MPP Voltage (Vmpp)	[V]	32.8	33.2	33.5
MPP Current (Impp)	[A]	8.46	8.48	8.49
Open Circuit Voltage (Voc)	[V]	39.3	39.4	39,4
Short Circuit Current (Isc)	[A]	9.09	9.13	9.16



LG370-380N1C-A6 AUSpdf

© 2020 LG Electronics USA, Inc. All rights reserved.

LG NeON[®]2



Preliminary

Electrical Properties (STC*)

Model		LG370N1C-A6	LG375N1C-A6	LG3B0N1C-A6
Maximum Power (Pmax)	[W]	370	375	380
MPP Voltage (Vmpp)	[V]	34.9	35.3	35.7
MPP Current (Impp)	[A]	10.61	10.63	10.65
Open Circuit Voltage (Voc. ± 5%)	[V]	41.7	41.8	41.9
Short Circuit Current (Isc, ± 5%)	[A]	11.31	11.35	11.39
Module Efficiency	[%]	20.4	20.7	21.0
Bifaciality Coefficient of Power	[%]		10	
Power Tolerance	[%]		0~+3	

Operating Conditions


Operating Temperature	[°C]	-40 ~+85
Maximum System Voltage	[v]	1,000
Maximum Series Fuse Rating	[A]	20
Mechanical Test Load* (Front)	[Pa/psf]	5,400
Mechanical Test Load* (Rear)	[Pa/psf]	4,000

*Based on IEC 61215-2: 2016 (Test Load = Design Loak x Safety Factor (1.5)) Mechanical Test Loads 6,000Pa / 5,400Pa based on IEC61215: 2005

Packaging Configuration

Number of Modules per Pallet	[EA]	25
Number of Modules per 40' Container	[EA]	650
Number of Modules per 53' Container	[EA]	850
Packaging Box Dimensions (L x W x H)	[mm]	1,790 x 1,120 x 1,213
Packaging Box Dimensions (L x W x H)	[in]	70.5 x 44.1 x 47.8
Packaging Box Gross Weight	[kg]	500
Packaging Box Gross Weight	[Ib]	1,102

Dimensions (mm/inch)



22171 MCH RD MANDEVILLE, LA 70471

CONTRACTOR

PHONE: 9152011490 PROJECT NAME & ADDRESS

KIM QUETEL

209 LAPAZ, LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

SHEET TITLE **RESOURCE DOCUMENT**

DRAWN DATE	1/21/2022
DRAWN BY	VI

SHEET NUMBER

Data Sheet Enphase Microinverters Region: AMERICAS

Enphase IQ 7 and IQ 7+ Microinverters

The high-powered smart grid-ready Enphase IQ 7 Micro™ and Enphase IQ 7+ Micro™ dramatically simplify the installation process while achieving the highest system efficiency.

Part of the Enphase IQ System, the IQ 7 and IQ 7+ Microinverters integrate with the Enphase IQ Envoy™, Enphase IQ Battery™, and the Enphase Enlighten™ monitoring and analysis software.

IQ Series Microinverters extend the reliability standards set forth by previous generations and undergo over a million hours of power-on testing, enabling Enphase to provide an industry-leading warranty of up to 25 years.



To learn more about Enphase offerings, visit enphase.com

Easy to Install

- · Lightweight and simple
- · Faster installation with improved, lighter two-wire cabling
- Built-in rapid shutdown compliant (NEC 2014 & 2017)

Productive and Reliable

- · Optimized for high powered 60-cell and 72-cell* modules
- · More than a million hours of testing
- · Class II double-insulated enclosure
- · UL listed

Smart Grid Ready

- · Complies with advanced grid support, voltage and frequency ride-through requirements
- · Remotely updates to respond to changing grid requirements
- · Configurable for varying grid profiles
- Meets CA Rule 21 (UL 1741-SA)
- * The IQ 7+ Micro is required to support 72-cell modules.

ENPHASE.

Enphase IQ 7 and IQ 7+ Microinverters INPUT DATA (DC) IQ7PLUS-72-2-US 235 W - 350 W + 235 W - 440 W + Commonly used module pairings' Module compatibility 60-cell PV modules only 60-cell and 72-cell PV module Maximum input DC voltage 48 V 60 V Peak power tracking voltage 27 V - 37 V 27 V - 45 V 16 V - 48 V 16 V - 60 V Operating range Min/Max start voltage 22 V / 48 V 22 V / 60 V 15 A Max DC short circuit current (module Isc) 15 A Overvoltage class DC port DC port backfeed current 0A 1 x 1 ungrounded array; No additional DC side protection required; PV array configuration AC side protection requires max 20A per branch circuit OUTPUT DATA (AC) 10 7 Microinverter 1Q 7+ Microinverter Peak output power 250 VA 295 VA Maximum continuous output power 240 VA 290 VA 240 V / 240 V / Nominal (L-L) voltage/range² 208 V / 208 V / 183-229 V 183-229 V 211-264 V 211-264 V 1.0 A (240 V) 1.15 A (208 V) 1.21 A (240 V) 1.39 A (208 Maximum continuous output current Nominal frequency 60 Hz 60 Hz Extended frequency range 47 - 68 Hz 47-68 Hz AC short circuit fault current over 3 cycles 5.8 Arms 5.8 Arms 16 (240 VAC) 13 (208 VAC) 13 (240 VAC) 11 (208 VAC) Maximum units per 20 A (L-L) branch circuit® Overvoltage class AC port AC port backfeed current DA O.A. 1.0 Power factor setting Power factor (adjustable) 0.85 leading ... 0.85 lagging EFFICIENCY @240 V @240 V @208 V @208 V 97.6% 97.6% 97,5% 97.3 % Peak efficiency CEC weighted efficiency 97.0 % 97.0 % 97.0 % 97.0 % MECHANICAL DATA -40°C to +65°C Ambient temperature range Relative humidity range 4% to 100% (condensing) Connector type (IQ7-60-2-US & IQ7PLUS-72-2-US) MC4 (or Amphenol H4 UTX with additional Q-DCC-5 adapter) 212 mm x 175 mm x 30.2 mm (without bracket) Dimensions (WxHxD) Weight 1.08 kg (2.38 lbs) Cooling Natural convection - No fans Approved for wet locations Pollution degree Enclosure Class II double-insulated, corrosion resistant polymeric enclosure NEMA Type 6 / outdoor Environmental category / UV exposure rating **FEATURES** Communication Power Line Communication (PLC) Monitoring Enlighten Manager and MyEnlighten monitoring options. Both options require installation of an Enphase IQ Envoy. Disconnecting means The AC and DC connectors have been evaluated and approved by UL for use as the load-break disconnect required by NEC 690. Compliance CA Rule 21 (UL 1741-SA) UL 62109-1, UL1741/IEEE1547, FCC Part 15 Class B, ICES-0003 Class B, CAN/CSA-C22.2 NO. 107.1-01 This product is UL Listed as PV Rapid Shut Down Equipment and conforms with NEC-2014 and

NEC-2017 section 690.12 and C22.1-2015 Rule 64-218 Rapid Shutdown of PV Systems, for AC

and DC conductors, when installed according manufacturer's instructions

- 1. No enforced DC/AC ratio. See the compatibility calculator at https://enphase.com/en-us/support/module-compatibility.
- Nominal voltage range can be extended beyond nominal if required by the utility.
 Limits may vary. Refer to local requirements to define the number of microinverte

To learn more about Enphase offerings, visit enphase.com

© 2019 Enphase Energy: All rights reserved. All trademarks or brands used are the property of Enphase Energy, Inc.



CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490 PROJECT NAME & ADDRESS

KIM QUETEL

209 LAPAZ, LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

> SHEET TITLE **RESOURCE DOCUMENT**

1/21/2022 DRAWN DATE DRAWN BY VI

SHEET NUMBER

Data Sheet Enphase Networking

Enphase IQ Combiner 3

(X-IQ-AM1-240-3)

The Enphase IQ Combiner 3™ with Enphase IQ Envoy™ consolidates interconnection equipment into a single enclosure and streamlines PV and storage installations by providing a consistent, pre-wired solution for residential applications. It offers up to four 2-pole input circuits and Eaton BR series busbar assembly.



Smart

- · Includes IQ Envoy for communication and control
- · Flexible networking supports Wi-Fi, Ethernet, or cellular
- · Optional AC receptacle available for PLC bridge
- · Provides production metering and optional consumption
- · Supports Ensemble Communications Kit for communication with Enphase Encharge™ storage and Enphase Enpower™ smart switch

Simple

- · Reduced size from previous combiner
- · Centered mounting brackets support single stud mounting
- · Supports back and side conduit entry
- · Up to four 2-pole branch circuits for 240 VAC plug-in breakers (not included)
- · 80 A total PV or storage branch circuits

Reliable

- · Durable NRTL-certified NEMA type 3R enclosure
- · Five-year limited warranty
- UL listed



Enphase IQ Combiner 3

MODEL NUMBER

IQ Combiner 3 IQ Combiner 3 with Enphase IQ Envoy™ printed circuit board for integrated revenue grade PV X-IQ-AM1-240-3 production metering (ANSI C12.20 +/- 0.5%) and optional* consumption monitoring (+/- 2.5%).

ACCESSORIES and REPLACEMENT PARTS (not included, order separately)

Enphase Mobile Connect CELLMODEM-03 (4G/12-year data plan) Consumption Monitoring* CT

Plug and play industrial grade cellular modem with data plan for systems up to 60 CELLMODEM-01 (3G/5-year data plan) microinverters. (Available in the US, Canada, Mexico, Puerto Rico, CELLMODEM-M1 (4G based LTE-M/5-year data plan) where there is adequate cellular service in the installation area.) microinverters. (Available in the US, Canada, Mexico, Puerto Rico, and the US Virgin Islands, Split core current transformers enable whole home consumption metering (+/- 2.5%).

CT-200-SPLIT ring is required for Enphase Storage Systems

Ensemble Communications Kit Installed at the IQ Envoy. For communications with Enphase Encharge™ storage and Enphase COMMS-KIT-01 Enpower™ smart switch. Includes USB cable for connection to IQ Envoy or Enphase IQ Combiner™ and allows wireless communication with Encharge and Enpower. Supports Eaton BR210, BR215, BR220, BR230, BR240, BR250, and BR260 circuit breakers. Circuit Breakers BRK-10A-2-240 Circuit breaker, 2 pole, 10A, Eaton BR210 BRK-15A-2-240 Circuit breaker, 2 pole, 15A, Eaton BR215 BRK-20A-2P-240 Circuit breaker, 2 pole, 20A, Eaton BR220 EPLC-01 Power line carrier (communication bridge pair), quantity - one pair XA-SOLARSHIELD-ES Replace the default solar shield with this Ensemble Combiner Solar Shield to match the look and feel of the Enphase Enpower™ smart switch and the Enphase Encharge™ storage system XA-PLUG-120-3 Accessory receptacle for Power Line Carrier in IQ Combiner 3 (required for EPLC-01) XA-ENV-PCBA-3 Replacement IQ Envoy printed circuit board (PCB) for Combiner 3

ELECTRICAL SPECIFICATIONS

nating	ooming do addy	
System voltage	120/240 VAC, 60 Hz	
Eaton BR series busbar rating	125 A	
Max. continuous current rating (output to grid)	65 A	
Max. fuse/circuit rating (output)	90 A	
Branch circuits (solar and/or storage)	Up to four 2-pole Eaton BR series Distributed Generation (DG) breakers only (not included)	
Max. continuous current rating (input from PV)	64 A	
Max. total branch circuit breaker rating (input)	80 A of distributed generation / 95 A with IQ Envoy breaker included	
Envoy breaker	10A or 15A rating GE Q-line/Siemens Type QP /Eaton BR series included	
Production Metering CT	200 A solid core pre-installed and wired to IQ Envoy	
MECHANICAL DATA		
Dimensions (WxHxD)	49.5 x 37.5 x 16.8 cm (19.5" x 14.75" x 6.63"). Height is 21.06" (53.5 cm with mounting brackets).	
Weight	7.5 kg (16.5 lbs)	
Ambient temperature range	-40° C to +46° C (-40° to 115° F)	
Cooling	Natural convection, plus heat shield	
Enclosure environmental rating	Outdoor, NRTL-certified, NEMA type 3R, polycarbonate construction	
Wire sizes	 20 A to 50 A breaker inputs: 14 to 4 AWG copper conductors 60 A breaker branch input: 4 to 1/0 AWG copper conductors Main lug combined output: 10 to 2/0 AWG copper conductors Neutral and ground: 14 to 1/0 copper conductors Always follow local code requirements for conductor sizing. 	
Altitude	To 2000 meters (6,560 feet)	

Continuous duty

INTERNET CONNECTION OPTION	NS	
Integrated Wi-Fi	802.11b/g/n	
Ethernet	Optional, 802.3, Cat5E (or Cat 6) UTP Ethernet cable (not included)	
Cellular	CELLMODEM-M1 4G based LTE-M cellular modem (not included). Note that an Enphase Mobil Connect cellular modem is required for all Ensemble installations.	
COMPLIANCE		
Compliance, Combiner	UL 1741, CAN/CSA C22.2 No. 107.1, 47 CFR, Part 15, Class B, ICES 003 Production metering: ANSI C12.20 accuracy class 0.5 (PV production)	
Compliance, IQ Envoy	UL 60601-1/CANCSA 22.2 No. 61010-1	

To learn more about Enphase offerings, visit enphase.com

© 2021 Enphase Energy. All rights reserved, Enphase, the Enphase logo, IQ Combiner 3, and other trademarks or service names are the trademarks of Enphase Energy, Inc. Data subject to change. 2021-05-20



CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490 PROJECT NAME & ADDRESS

KIM QUETEL

209 LAPAZ, LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

> SHEET TITLE RESOURCE **DOCUMENT**

1/21/2022 DRAWN DATE **DRAWN BY** VI


SHEET NUMBER


R-003





To learn more about Enphase offerings, visit enphase.com





SUNPR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490

PROJECT NAME & ADDRESS
KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY


SYSTEM SIZE


DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

SHEET TITLE RESOURCE DOCUMENT

DRAWN DATE 1/21/2022
DRAWN BY VI

SHEET NUMBER





REVISION DATE: 10/3/2019

LEGAL NOTICE

SHEET

WWW.UNIRAC.COM

CONTRACTOR SUNPR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490

PROJECT NAME & ADDRESS
KIM QUETEL

209 LAPAZ,LAKE CITY, FL 32024

COUNTY:-COLUMBIA COUNTY

SYSTEM SIZE


DC SIZE: 11.625 KW DC-(STC)
AC SIZE: 8.990 KW AC


SHEET TITLE

RESOURCE DOCUMENT

DRAWN DATE 1/21/2022
DRAWN BY VI

SHEET NUMBER





PART & ASSEMBLY

BONDING SPLICE

BAR

9/27/2017

NOMINAL

PRODUCT PROTECTED BY

ONE OR MORE US PATENTS

LEGAL NOTICE

SHEET

DRAWING TYPE:

REVISION DATE:

1411 BROADWAY BLVD, NE

PHONE: 505.242.6411

WWW,UNIRAC.COM

ALBUQUERQUE, NM 87102 USA DESCRIPTION:

SHEET TITLE **RESOURCE DOCUMENT**

CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490 PROJECT NAME & ADDRESS


KIM QUETEL


209 LAPAZ,LAKE CITY,

FL 32024 **COUNTY:-COLUMBIA COUNTY** SYSTEM SIZE DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

DRAWN DATE 1/21/2022 DRAWN BY VI

SHEET NUMBER





1411 BROADWAY BLVD. NE ALBUQUERQUE, NM 87102 USA PHONE: 505.242.6411 WWW.UNIRAC.COM

PRODUCT LINE: SOLARMOUNT DRAWING TYPE: PART DETAIL DESCRIPTION: STANDARD RAIL 9/11/2017 REVISION DATE:

DRAWING NOT TO SCALE ALL DIMENSIONS ARE NOMINAL

PRODUCT PROTECTED BY ONE OR MORE US PATENTS LEGAL NOTICE

SHEET

DRAWN DATE 1/21/2022 DRAWN BY

SHEET NUMBER

SHEET TITLE

RESOURCE

DOCUMENT

VI

CONTRACTOR

22171 MCH RD

MANDEVILLE, LA 70471


PHONE: 9152011490 PROJECT NAME & ADDRESS


KIM QUETEL


209 LAPAZ,LAKE CITY, FL 32024

> **COUNTY:-COLUMBIA COUNTY** SYSTEM SIZE

DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC









302022C

302022D

302023C

302023D

303024C

302024D 302025C

302025D

302026C

302026D

SM ENDCLAMP C DRK AL

SM ENDCLAMP D CLR AL

SM ENDCLAMP D DRK AL

SM ENDCLAMP E CLR AL

SM ENDCLAMP E DRK AL

SM ENDCLAMP F CLR AL

SM ENDCLAMP F DRK AL

SM ENDCLAMP K CLR AL

SM ENDCLAMP K DRK AL

1411 BROADWAY BLVD. NE ALBUQUERQUE, NM 87102 USA PHONE: 505.242.6411 WWW.UNIRAC.COM

PRODUCT LINE: SOLARMOUNT DRAWING TYPE: PART DETAIL END CLAMPS -DESCRIPTION: TOP MOUNTING 9/27/2017 REVISION DATE:

DRAWING NOT TO SCALE ALL DIMENSIONS ARE NOMINAL

PRODUCT PROTECTED BY ONE OR MORE US PATENTS LEGAL NOTICE

S

SHEET

DOCUMENT DRAWN DATE | 1/21/2022 DRAWN BY VI

SHEET TITLE

RESOURCE

CONTRACTOR

22171 MCH RD MANDEVILLE, LA 70471

PHONE: 9152011490

PROJECT NAME & ADDRESS

KIM QUETEL

209 LAPAZ,LAKE CITY,

FL 32024

COUNTY:-COLUMBIA COUNTY SYSTEM SIZE DC SIZE: 11.625 KW DC-(STC) AC SIZE: 8.990 KW AC

SHEET NUMBER